

#### **DATA SHEET**

# FS65HDA Heavy Duty Accelerometer

#### **SPECIAL FEATURES**

- Intrinsically immune to EMI
- Electrically passive
- · Compact design and low weight
- Designed for application on pantographs
- EN45545 certified



#### **DESCRIPTION**

The FS65HDA Heavy Duty Accelerometer is a Fiber Bragg Grating (FBG) based single-axis acceleration sensor, designed to be directly fixed with screws. It is suited for high voltage and harsh environments commonly found in railway applications, namely in vehicle pantographs. It operates with two FBG for effective temperature compensation and can be inserted in series with other sensors as it is provided with two lead fibers.

The FS65HDA is based on the newLight® technology developed by HBK FiberSensing. newLight sensors em-

ploy high strength fiber coatings ensuring robustness, increased sensitivity, and higher measurement accuracy. HBK FiberSensing offers innovative sensor designs compatible with standard telecommunication fibers. This eases network design and significantly reduces installation time and cost, even when a large number of sensors are multiplexed on the same fiber, sometimes kilometers apart. The technology is completely passive fitting explosive environments, self-referenced (providing measurement long term stability), and compatible with most interrogators in the market.

### **BENEFITS AND APPLICATION**


#### Sensor design

- High robustness and reliability ensured by innovative sensor design, careful selection of materials and compact packaging
- No need for temperature compensation with external elements
- Possibility to connect in series with other FBG sensors on a single optical fiber
- Specifications compatible with railway applications

#### Fiber Bragg grating technology

- No drift, absolute referenced measurements
- Immune to electro-magnetic and radio frequency interferences
- Passive technology fitting applications in explosive areas
- Reduced cable requirements with intrinsic multiplexing capability
- Long distances between sensors and the interrogators attainable
- Combinable with other FBG sensor types on the same fiber and same interrogator

B05904 02 E00 01 10.09.2024 1



## **SPECIFICATIONS**

Sensor		
Sensitivity per FBG <sup>1)</sup>	pm/g	40
Calibration factor <sup>2)</sup>	g/nm	12.5
Resolution <sup>3)</sup>	mg	< 2
Measurement range	g	± 20
Limit acceleration	g	± 100
Transverse sensitivity	%	< 1
Frequency range	Hz	0.5 200
Resonance frequency	Hz	790
Flatness <sup>4)</sup>	%	< 10
Typical frequency response	n.a.	Maxwill (RB) -10 FBG1 FBG2 FBG2 FBG2 FFBG2 FFBC2 FFBG2 FFBG2 FFBC2

B05904 02 E00 01 10.09.2024 2

Operation temperature range	°C	-40 75
Storage temperature range	°C	-40 75
Temperature effect on sensitivity <sup>5)</sup>	%	<10
Dimensions	mm	54.5 x 49.2 x 15.5
Weight		
Sensor, not considering cable	g	34
Sensor with cable and connectors		620
Main Materials <sup>6)</sup>	n.a.	Aluminum
Bragg wavelengths	nm	1560 and 1570
Fiber type	n.a.	SMF-28 compatible
Fiber cladding and coating diameter	μm	125/155
FWHM, reflectivity and side lobe suppression	n.a.	≤ 0.3 nm, 21 ± 4 %, 10 dB
Inputs / Outputs		
Cable	n.a.	Dual fiber, EN45545 compliant outer coating, Ø 7.5 mm, metal free
Cable length <sup>7)</sup>	m	8
Cable bend radius	mm	> 40
Connector	n.a.	Huber+Suhner Q-ODC-2

<sup>1)</sup> Typical wavelength variation of each FBG caused by a 1 g acceleration.

# **ORDER INFORMATION**

## **Standard Item**

1-FS0EM-1701-02-01

<sup>2)</sup> Typical value. Calibration factor defined as acceleration / wavelength difference (λ2 - λ1). Calibration is performed at 100 Hz.

<sup>3)</sup> Dynamic signals obtained with FFT analysis using an MXFS interrogator for wavelength measurement using catman®.

<sup>4)</sup> Relative sensitivity variation <10% up to 200 Hz. Typical variation is 20% up to 350 Hz.

<sup>5)</sup> Over the full operating temperature range and frequency range.

<sup>6)</sup> The full composition of the sensor including cable, complies with RoHS, REACH, Conflict Minerals.

<sup>7)</sup> With a tolerance of ±20 cm. For different cable lengths please contact HBK FiberSensing.